RSPCB Series Precision PCB-Mounted Current Resistor/Shunts 10 Amp to 150 Amp






- 50mV Standard Output Custom Available
- ± 0.25% Standard Tolerance (± 0.1% available)
- Non-Inductive Manganin Element
- Compact size
- TCR of ± 15PPM
- · Heat-treated for Stability



RSPCB	Amperes (50mV Output)										
	10	15	20	25	30	40	50	75	100	125	150
Power (W)	0.5	0.75	1.0	1.25	1.5	2.0	2.5	3.8	5	6.3	7.5
Resistance (mOhms)	5.0	3.333	2.5	2.0	1.667	1.25	1.0	0.6667	0.5	0.4	0.3333
"A" Height in[mm] ±0.03 [0.8]	0.13 [3.3]	0.20 [5.1]	0.26 [6.6]	0.34 [8.6]	0.24 [6.1]	0.32 [8.1]	0.42 [10.7]	0.58 [14.7]	0.44 [11.2]	0.66 [17.8]	0.80 [20.3]
Thickness in[mm] ±0.002 [0.05]	0.0253" [0.64]				0.040" [1.0]				0.079" [2.0]		



Ordering Information

You may order by description (see above chart) or part number:

Example Part Number: **RSPCB-30-T** PART TYPE - NOMINAL CURRENT - CONTACT PLATING (optional)


A Riedon Customer Service representative will confirm your decription and provide a part number on a quote or sales order. You may use this part number for future orders.

© Riedon, Inc.

300 Cypress Avenue www.riedon.com

Alhambra CA 91801 sales@riedon.com

RSPCB Series Precision PCB-Mounted Current Resistor/Shunts 10 Amp to 150 Amp




TECHNICAL NOTES


Mounting: The manganin blade must never exceed +145°C (125°C recommended), otherwise permanent resistance change may occur. Shunts should be mounted in a manner that promotes free convectional airflow or use forced air cooling.

If the shunt is mounted in an enclosure, care must be taken to ensure adequate cooling. If the power density is greater than 1/4 watt per square inch of the enclosure surface for all enclosed devices, additional cooling must be supplied in the form of air vents or fans.

Pulse Operation: Shunts that do not need continuous operation and are only exposed to intermittent pulses can be operated at levels above their rated current for short periods of times. Pulses are limited to the maximum temperature of the blades not exceeding 145°C (125°C recommended). Many variables such as ambient temperature, cross section of the current carrying conductors, and pulse duration make calculating exact values difficult. Shunt current will need to be validated by customer for pulse current and duty cycle on a case by case basis.







300 Cypress Avenue www.riedon.com

Alhambra CA 91801 sales@riedon.com